

Maximator AIM Nitrogen Generator Column Outputs

Flow based upon % purity of Nitrogen gas											
Model	Column size	No of column pairs	Flow	95%	96%	97%	98%	99%	99.5%	99.9%	99.95%
G200	1000	2	SCFM	9.43	8.58	8.37	7.06	6	4.94	3.43	3.07
G300	100	3	SCFM	14.13	12.89	12.54	10.59	9.01	7.42	5.12	4.59
G450	1400	3	SCFM	21.37	19.42	18.89	16.07	13.6	11.12	7.77	6.88
G600	1400	4	SCFM	28.5	25.89	25.18	21.44	18.12	14.83	10.35	9.18
G750	1400	5	SCFM	35.6	32.38	31.5	26.79	22.67	18.54	12.96	11.48
G900	1400	6	SCFM	42.73	38.85	37.79	32.14	27.19	22.25	15.54	13.77